

## 1.8 Volt Technology - Benefits

Portability is and will continue to be one of the key features driving the design and development of new electronic equipment. Existing products such as palmtop computers, cellular phones and data acquisition devices are becoming increasingly smaller and more powerful. Handheld markets will demand that product feature sets be enhanced and that battery operating life be increased. These market requirements, in turn, will put more demands on battery and integrated circuit technology.

In order to optimize battery technology ICs must be able to operate at voltages well below the 5V range that most ICs operate at today. In fact, even integrated circuits operating at 3 volts do not make the most of the available battery technology. Thus the need for devices that operate below 3 volts.

### BATTERY TECHNOLOGY OVERVIEW

#### Primary versus Secondary

In portable or handheld equipment there are two major battery types employed; primary and secondary. Primary cells are disposable, and alkaline and lithium cells are the main primary batteries in use today. Alkaline batteries are extremely common in consumer applications such as electronic games, cordless phones and palmtop computers. While lithium batteries are used as a primary power source in other consumer products such as cameras and as a back-up supply in palmtops.

Secondary cells are rechargeable batteries. Among the many secondary cells available, lead-acid, Ni-cad and Nickel Metal Hydride (NMH) are the most popular.

#### Voltage Ratings

Batteries for portable applications, whether primary or secondary, have three different voltage ratings; Rated or nominal, Operating, and End-of-life. The rated voltage is usually the open circuit voltage, which in the case of alkaline "AA" cells is 1.5V. Under normal load the "operating voltage" is realized and in all cases is less than the nominal voltage. The final battery voltage rating

is the end-of-life voltage, which is defined as the voltage at which 100% of the usable power of the battery is consumed, or as 75% of the operating voltage. In the case of the same alkaline battery the end-of-life voltage is 0.9 volts. Table 1 lists the operating and end-of-life voltages for a single "AA" or equivalent cell of the five battery types mentioned above.

**TABLE 1 - BATTERY VOLTAGE SUMMARY**

BATTERY TYPE	OPERATING VOLTAGE	END-OF-LIFE VOLTAGE
ALKALINE	1.2V	0.9V
LITHIUM	2.7V	2.0V
LEAD-ACID	2.0V	1.75V
NI-CAD	1.2V	0.9V
NMH	1.2V	1.0V

With applications employing primary cells this means that batteries are replaced less often, thus reducing operating cost as well as having a positive effect on the environment due to the use and disposal of fewer batteries. In systems with secondary cells time between recharging increased, thus enhancing the performance of the product.

### LOW VOLTAGE APPLICATIONS

As mentioned previously, the need for increased portability will drive the employment of low voltage technology. Portable and handheld applications requiring low voltage (sub 3V) technology will be numerous and will in many cases be high volume. These include a variety of personal communications devices such as cellular and cordless phones, computing devices like palmtops and portable PCs, and a number of data acquisition devices for a variety of medical, industrial and commercial applications.

# 1.8 Volt Technology - Benefits

---

## MICROCHIP'S LOW VOLTAGE PRODUCT POSITION

Prior to the announcement of a family of 1.8V Serial EEPROMs in November of 1992, Microchip had already established itself as a leader in low voltage semiconductor products. Microchip's current product portfolio consists of: (1) Serial EEPROMs that operate, both READ and WRITE, down to the following voltage levels: 1.8V, 2.0V, 2.5V and 5V; (2) ROM based microcontrollers that operate down to 2V; and (3) 3V One Time Programmable EPROMs.

The 1.8V Serial EEPROM family operates down to 1.8V without the relaxation of any specification. This includes all AC, DC retention and endurance parameters. Currently the 1.8V family consists of three 3-wire devices, in densities ranging from 1K to 4K bits. Packaging options include 8 pin SOIC and 8 pin PDIP devices. Typical

operating currents for these devices, at 1.8V, are in the 70uA range, resulting in power consumption levels of less than 150uW. This compares to 1 to 5 mW for comparable devices operating at 5V. In the near future, the 1.8V family of Serial EEPROMs will be expanded to include all 2-wire devices.

## SUMMARY

With the introduction of 1.8V Serial EEPROMs, Microchip has made available silicon technology that optimizes existing battery technology. This over time will result in the development, production, marketing and application of more portable and higher performance handheld and portable computing, telecommunications, and data acquisition products.

*Author: Tom Tyson  
Memory Products Division*

---

---

# WORLDWIDE SALES & SERVICE

---

---

## AMERICAS

### Corporate Office

Microchip Technology Inc.  
2355 West Chandler Blvd.  
Chandler, AZ 85224-6199  
Tel: 602 786-7200 Fax: 602 786-7277  
Technical Support: 602 786-7627  
Web: <http://www.mchip.com/microhip>

### Atlanta

Microchip Technology Inc.  
500 Sugar Mill Road, Suite 200B  
Atlanta, GA 30350  
Tel: 770 640-0034 Fax: 770 640-0307

### Boston

Microchip Technology Inc.  
5 Mount Royal Avenue  
Marlborough, MA 01752  
Tel: 508 480-9990 Fax: 508 480-8575

### Chicago

Microchip Technology Inc.  
333 Pierce Road, Suite 180  
Itasca, IL 60143  
Tel: 708 285-0071 Fax: 708 285-0075

### Dallas

Microchip Technology Inc.  
14651 Dallas Parkway, Suite 816  
Dallas, TX 75240-8809  
Tel: 214 991-7177 Fax: 214 991-8588

### Dayton

Microchip Technology Inc.  
35 Rockridge Road  
Englewood, OH 45322  
Tel: 513 832-2543 Fax: 513 832-2841

### Los Angeles

Microchip Technology Inc.  
18201 Von Karman, Suite 455  
Irvine, CA 92715  
Tel: 714 263-1888 Fax: 714 263-1338

### New York

Microchip Technology Inc.  
150 Motor Parkway, Suite 416  
Hauppauge, NY 11788  
Tel: 516 273-5305 Fax: 516 273-5335

## AMERICAS (continued)

### San Jose

Microchip Technology Inc.  
2107 North First Street, Suite 590  
San Jose, CA 95131  
Tel: 408 436-7950 Fax: 408 436-7955

## ASIA/PACIFIC

### Hong Kong

Microchip Technology  
Unit No. 3002-3004, Tower 1  
Metroplaza  
223 Hing Fong Road  
Kwai Fong, N.T. Hong Kong  
Tel: 852 2 401 1200 Fax: 852 2 401 3431

### Korea

Microchip Technology  
168-1, Youngbo Bldg. 3 Floor  
Samsung-Dong, Kangnam-Ku,  
Seoul, Korea  
Tel: 82 2 554 7200 Fax: 82 2 558 5934

### Singapore

Microchip Technology  
200 Middle Road  
#10-03 Prime Centre  
Singapore 188980  
Tel: 65 334 8870 Fax: 65 334 8850

### Taiwan

Microchip Technology  
10F-1C 207  
Tung Hua North Road  
Taipei, Taiwan, ROC  
Tel: 886 2 717 7175 Fax: 886 2 545 0139

## EUROPE

### United Kingdom

Arizona Microchip Technology Ltd.  
Unit 6, The Courtyard  
Meadow Bank, Furlong Road  
Bourne End, Buckinghamshire SL8 5AJ  
Tel: 44 0 1628 851077 Fax: 44 0 1628 850259

### France

Arizona Microchip Technology SARL  
2 Rue du Buisson aux Fraises  
91300 Massy - France  
Tel: 33 1 69 53 63 20 Fax: 33 1 69 30 90 79

### Germany

Arizona Microchip Technology GmbH  
Gustav-Heinemann-Ring 125  
D-81739 Muenchen, Germany  
Tel: 49 89 627 144 0 Fax: 49 89 627 144 44

### Italy

Arizona Microchip Technology SRL  
Centro Direzionale Colleoni  
Palazzo Pegaso Ingresso No. 2  
Via Paracelso 23, 20041  
Agrate Brianza (MI) Italy  
Tel: 39 039 689 9939 Fax: 39 039 689 9883

## JAPAN

Microchip Technology Intl. Inc.  
Benex S-1 6F  
3-18-20, Shin Yokohama  
Kohoku-Ku, Yokohama  
Kanagawa 222 Japan  
Tel: 81 45 471 6166 Fax: 81 45 471 6122

9/22/95

All rights reserved. © 1995, Microchip Technology Incorporated, USA.

Information contained in this publication regarding device applications and the like is intended through suggestion only and may be superseded by updates. No representation or warranty is given and no liability is assumed by Microchip Technology Incorporated with respect to the accuracy or use of such information, or infringement of patents or other intellectual property rights arising from such use or otherwise. Use of Microchip's products as critical components in life support systems is not authorized except with express written approval by Microchip. No licenses are conveyed, implicitly or otherwise, under any intellectual property rights. The Microchip logo and name are registered trademarks of Microchip Technology Inc. All rights reserved. All other trademarks mentioned herein are the property of their respective companies.